

Datasheet of Remote Control

Model No.: EF-BBRC07

Specifications:

Item name	Remote Control
Weight	About 40g
Size	68*36*15MM
Buttons Sum	1 - 4 Keys
Code Type	Self-copy
Voltage	DC 2*3V CR2016 battery)
Operating Frequency	433Mhz
Faceplate Useful Lifespan	Above 20000 times
Transmission distance	50~100M
Ambient Temperature	'-10°C ~ +60°C
Application	Remote control garage doors,electric doors and Windows, anti-theft alarm, remote control switch, industrial control, etc..

Feature:

1. Chips Could be Copied

2260(all manufacturers);2262(All manufacturers);PT2264, 5326(All manufacturers);SC5262, HT600, HT680, HT6207, HT6010, HT6012, HT6014, SMC918series,527(All manufacturers);1527(All manufacturers);2240(All manufacturers);HCS101, HCS200\HCS201(part code),HCS300\HCS301, part single chip microcomputer.....

2.Code Cleaning Method:

Press the unlock button and lock button at the same time(some shells are the up button and down button), after the LED indicator light flashes three times, loosen any one of the buttons while the other is kept pressing, then push the released button three times, the LED indicator will enter into the fast flashing status. At this time all the memory data is cleared, the cleaned remote control will not have lighting LED indicator no matter which button you press.

3. Copy Method:

One hand keeps the original remote controller, while another keeps the copy remote control, the two remote controls should be placed as closely as possible (the ideal situation is to put the two remote controls on the desktop side by side with zero distance), respectively press down the copy button, when the LED indicator light flashes quickly after three flashes, this copy is successful, other key operating

methods are the same. Some remote control has a smaller transmitting power, so the original remote control should be placed back to the copy remote control to be operated. For the presence of noise, it should avoid interference to operate, If the copy is not successful, it should recopy after clearing code.(Attention:Your original remote control must be able to work and the same as our remote control frequency)

OEM/ODM Customization:

1. Button Labels: ABCD / 1234 / Lock, Unlock, Stop, Alarm / others.
2. Color: As shown in photo, some model has multiple colors to choose.
3. Brand Logo: Brand logo print / etching available for customize orders, Pls contact us for details.

Application

