

Enterprise Gateway/ Controller

Pulsar Uniti Smart Gateway 256

SERIES

Indoor

Models

Pulsar Uniti Smart Gateway 256



MAIN FEATURES

- 1 Multi-WAN and multi-WAN port load balancing
- 2 Support cloud access
- 3 Manange 256PCS AP
- 4 Intelligent flow control
- **5** Remote management
- 6 Enterprise level gigabit routing gateway
- High performance architecture provides a better network experience
- 8 High reliability. Safe and stable
- Easy operation and maintenance
- 10 Cloud Platform
- 11 Business integration to meet diversified needs
- 12 Meet multi scenario applications
- (3) Outstanding performance, comprehensive safety protection





Pulsar Uniti Smart Gateway 256

| Model | Pulsar Uniti Smart Gateway 256 |
|-------------------------|--|
| Hardware Specifications | <u> </u> |
| DDR3L | 512M |
| Flash | 16M |
| Heat Dissipation | Natural heat dissipation |
| Interface | 4*Gigabit LAN (can be configured to multi WAN) |
| | 1*Gigabit WAN |
| | 1*Console |
| | 1*USB3.0 |
| Power | DC: 12V |
| Size | 440 *219 *44mm |
| Norking Temperature | 0°C~50°C |
| Storage Temperature | -40°C ~70°C |
| Working Humidity | 5%∼97%RH (No condensation) |
| | , |
| Software function | |
| AP manage | The maximum number of managed users is 128 users |
| | The AP management number is 128 units |
| | Centralized and remote management, to configure the wireless AP |
| Equipment overview | Total number of users, current links, online devices, and offline devices |
| | On-access real-time rate, running time, user management, device management |
| | Equipment information, equipment description, Intranet information, extranet information |
| Device management | List of equipment |
| | Template Settings |
| | Device upgrade |
| | Service configuration |
| | IPTV set up |
| | Automatic roaming |
| User management | User list |
| | User speed limit |
| Security center | IP filter |
| | MAC filter |
| | Website filtering |
| | Port mapped |
| | DMZ set up |
| Network function | Connection mode: static address, dynamic acquisition (DHCP), broadband dial (PPPOE), bypass mode |
| | DHCP server: either built-in DHCP server or external DHCP server |
| | Cloud platform server |
| System management | Backup Configuration Information |
| | Restore configuration information |
| | Factory data reset |
| | Restart immediately |
| | Firmware upgrade |
| | Time management includes the system display time and time synchronization |
| | System log |